

LINKSYS PAP2T(fax)

Zakładka Line1/Line2

Sekcja „Audio Configuration”

Zalecane ustawienia do faxu:

Pierwsza Opcja:

preferred codec: G711u
Echo Canc Adapt Enable: no
Echo Supp Enable: no
Fax CED Detect Enable: yes
Fax CNG Detect Enable: yes
Fax Passtru Codec: G711a
Fax Passtru Method: NSE
Fax Process NSE: Yes
Silence Supp Enable: No
Echo Canc Enable: no
Fax Codec Symetric: yes

Druga Opcja:

Silence Supp Enable:no
Silence Threshold:medium
Echo Canc Enable:no
Echo Canc Adapt Enable:no
Echo Supp Enable:no
FAX CED Detect Enable:yes
FAX CNG Detect Enable:yes
FAX Passtru Codec:G711u
FAX Codec Symmetric:no
FAX Passtru Method:None
FAX Process NSE: no

Audio Configuration	
Preferred Codec:	<input type="text" value="G711u"/>
Use Pref Codec Only:	<input type="text" value="no"/>
G729a Enable:	<input type="text" value="yes"/>
G723 Enable:	<input type="text" value="yes"/>
G726-16 Enable:	<input type="text" value="yes"/>
G726-24 Enable:	<input type="text" value="yes"/>
G726-32 Enable:	<input type="text" value="yes"/>
G726-40 Enable:	<input type="text" value="yes"/>
DTMF Process INFO:	<input type="text" value="yes"/>
DTMF Process AVT:	<input type="text" value="yes"/>
DTMF Tx Method:	<input type="text" value="Auto"/>
Hook Flash Tx Method:	<input type="text" value="None"/>
Release Unused Codec:	<input type="text" value="yes"/>
Silence Supp Enable:	<input type="text" value="no"/>
Silence Threshold:	<input type="text" value="medium"/>
Echo Canc Enable:	<input type="text" value="yes"/>
Echo Canc Adapt Enable:	<input type="text" value="yes"/>
Echo Supp Enable:	<input type="text" value="yes"/>
FAX CED Detect Enable:	<input type="text" value="yes"/>
FAX CNG Detect Enable:	<input type="text" value="yes"/>
FAX Passtru Codec:	<input type="text" value="G711u"/>
FAX Codec Symmetric:	<input type="text" value="yes"/>
FAX Passtru Method:	<input type="text" value="NSE"/>
FAX Process NSE:	<input type="text" value="yes"/>
FAX Disable ECAN:	<input type="text" value="no"/>

usuwanie efektu echa